Bergelectric Corp.
13650 NE Whitaker Way, Portland, OR 97230
(503) 255-1818

PANEL: STUDIO MOUNTING: RECESSED BUS: 125 A MLO
LOCATION: VARIES VOLTS: 208 PHASE: 1 WIRE: 3

DESCRIPTION	A/P	NO.	Ø	Ø	NO.	A/P	DESCRIPTION
KITCHEN "A"	20/1 *	1	A	A	2	40/2	RANGE
KITCHEN "B"	20/1 *	3	B	B	4	-	RANGE
DISHWASHER	20/1 *	5	A	A	6	30/2	DRYER
DISPOSAL	20/1 *	7	B	B	8	-	DRYER
MICRO / HOOD	20/1 *	9	A	A	10	15/2	MECH UNIT #
GEN LTS & PLUGS	15/1 *	11	B	B	12	-	MECH UNIT #
SPACE	-	13	A	A	14	20/1 *	BATHROOM
SPACE	-	15	B	B	16	20/1 *	WASHER
SPACE	-	17	A	A	18	-	SPACE
SPACE	-	19	B	B	20	-	SPACE
SPACE	-	21	A	A	22	20/2	WALL HEATER
SPACE	-	23	B	B	24	-	WALL HEATER

* = COMBINATION AFCI/GFCI CIRCUIT BREAKER TYPE

REFER TO ENLARGED UNIT PLANS FOR MECHANICAL UNIT CALL OUT.
PROVIDE CIRCUIT BREAKER AS INDICATED IN CHART BELOW:

CALL OUT	CIRCUIT BREAKER
PTHP-1	15A/1P
PTHP-2	15A/1P
PTHP-3	15A/1P
PTHP-4	15A/1P
PTHP-5	20A/1P
PTHP-6	30A/1P

Bergelectric Corp
13650 NE Whitaker Way, Portland, OR 97230
(503) 255-1818

PANEL: 1 BDRM MOUNTING: RECESSED BUS: 125 A MLO
LOCATION: VARIES VOLTS: 208 PHASE: 1 WIRE: 3

DESCRIPTION	A/P	NO.	Ø	Ø	NO.	A/P	DESCRIPTION
KITCHEN "A"	20/1 *	1	A	A	2	40/2	RANGE
KITCHEN "B"	20/1 *	3	B	B	4	-	RANGE
DISHWASHER	20/1 *	5	A	A	6	30/2	DRYER
DISPOSAL	20/1 *	7	B	B	8	-	DRYER
MICRO / HOOD	20/1 *	9	A	A	10	15/2	MECH UNIT #
GEN LTS & PLUGS	15/1 *	11	B	B	12	-	MECH UNIT #
BED LTS & PLUGS	15/1 *	13	A	A	14	20/1 *	BATHROOM
SPACE	-	15	B	B	16	20/1 *	WASHER
SPACE	-	17	A	A	18	-	SPACE
SPACE	-	19	B	B	20	-	SPACE
SPACE	-	21	A	A	22	20/2	WALL HEATER
SPACE	-	23	B	B	24	-	WALL HEATER

* = COMBINATION AFCI/GFCI CIRCUIT BREAKER TYPE

REFER TO ENLARGED UNIT PLANS FOR MECHANICAL UNIT CALL OUT.
PROVIDE CIRCUIT BREAKER AS INDICATED IN CHART BELOW:

CALL OUT	CIRCUIT BREAKER
PTHP-1	15A/1P
PTHP-2	15A/1P
PTHP-3	15A/1P
PTHP-4	15A/1P
PTHP-5	20A/1P
PTHP-6	30A/1P

Bergelectric Corp
13650 NE Whitaker Way, Portland, OR 97230
(503) 255-1818

PANEL: LOFT MOUNTING: RECESSED BUS: 125 A MLO
LOCATION: VARIES VOLTS: 208 PHASE: 1 WIRE: 3

DESCRIPTION	A/P	NO.	Ø	Ø	NO.	A/P	DESCRIPTION
KITCHEN "A"	20/1 *	1	A	A	2	40/2	RANGE
KITCHEN "B"	20/1 *	3	B	B	4	-	RANGE
DISHWASHER	20/1 *	5	A	A	6	30/2	DRYER
DISPOSAL	20/1 *	7	B	B	8	-	DRYER
MICRO / HOOD	20/1 *	9	A	A	10	15/2	MECH UNIT #
GEN LTS & PLUGS	15/1 *	11	B	B	12	-	MECH UNIT #
BED LTS & PLUGS	15/1 *	13	A	A	14	20/1 *	BATHROOM
SPACE	-	15	B	B	16	20/1 *	WASHER
SPACE	-	17	A	A	18	-	SPACE
SPACE	-	19	B	B	20	-	SPACE
SPACE	-	21	A	A	22	20/2	WALL HEATER
SPACE	-	23	B	B	24	-	WALL HEATER

* = COMBINATION AFCI/GFCI CIRCUIT BREAKER TYPE

REFER TO ENLARGED UNIT PLANS FOR MECHANICAL UNIT CALL OUT.
PROVIDE CIRCUIT BREAKER AS INDICATED IN CHART BELOW:

CALL OUT	CIRCUIT BREAKER
PTHP-1	15A/1P
PTHP-2	15A/1P
PTHP-3	15A/1P
PTHP-4	15A/1P
PTHP-5	20A/1P
PTHP-6	30A/1P

Bergelectric Corp
13650 NE Whitaker Way, Portland, OR 97230
(503) 255-1818

PANEL: 2 BDRM MOUNTING: RECESSED BUS: 125 A MLO
LOCATION: VARIES VOLTS: 208 PHASE: 1 WIRE: 3

DESCRIPTION	A/P	NO.	Ø	Ø	NO.	A/P	DESCRIPTION
KITCHEN "A"	20/1 *	1	A	A	2	40/2	RANGE
KITCHEN "B"	20/1 *	3	B	B	4	-	RANGE
DISHWASHER	20/1 *	5	A	A	6	30/2	DRYER
DISPOSAL	20/1 *	7	B	B	8	-	DRYER
MICRO / HOOD	20/1 *	9	A	A	10	15/2	MECH UNIT #
GEN LTS & PLUGS	15/1 *	11	B	B	12	-	MECH UNIT #
BED LTS & PLUGS	15/1 *	13	A	A	14	20/1 *	BATHROOM
BED LTS & PLUGS	15/1 *	15	B	B	16	20/1 *	WASHER
SPACE	-	17	A	A	18	-	SPACE
SPACE	-	19	B	B	20	-	SPACE
SPACE	-	21	A	A	22	20/2	WALL HEATER
SPACE	-	23	B	B	24	-	WALL HEATER

* = COMBINATION AFCI/GFCI CIRCUIT BREAKER TYPE

REFER TO ENLARGED UNIT PLANS FOR MECHANICAL UNIT CALL OUT.
PROVIDE CIRCUIT BREAKER AS INDICATED IN CHART BELOW:

CALL OUT	CIRCUIT BREAKER
PTHP-1	15A/1P
PTHP-2	15A/1P
PTHP-3	15A/1P
PTHP-4	15A/1P
PTHP-5	20A/1P
PTHP-6	30A/1P

Branch Panel

PANEL: 2H2A — MKE & ASSOCIATES, INC. — **MOUNTING:** SURFACE
FED BY: SDP-A — **BUS/MAIN** 200 MLO
LOC: — **VOLTS** 120/208 — **PHASE** 3 — **WIRE** 4

C	DESCRIPTION	A/P	No.	A	B	C	A	B	C	No.	A/P	DESCRIPTION	C
2	R-UTILITY U200 / CORR 200 / BIKE 204	20/1	1	720			2000			2	30/3	WH-2	5
2; 5	R-BIKE STORAGE 204	20/1	3		886			2000		4	--	--	--
2; 5	R-BIKE 204 / UTILITY 206 / IRRIG CONTROLLER	20/1	5			560			2000	6	--	--	--
2	R-AMENITY 210 / CORR 200	20/1	7	360			215			8	20/1	RCP-2	6
2	R-AMENITY 210	20/1	9		720			176		10	20/1	L-ROOMS 208 / 212 / 214 / 216-218 / 223 / 225	1
			11						326	12	20/1	L-AMENITY 215	1
			13				397			14	20/2	FC-1-1 / FC-1-3	5
2	R-AMENITY 220	20/1	15		720			397		16	--	--	--
2	FLR BOX - AMENITY 220	20/1	17			720			700	18	20/2	FC-1-3 / FC-1-5	5
2	FLR BOX - AMENITY 220	20/1	19	720			700			20	--	--	--
2	R-RR 213 / AMENITY 215	20/1	21		900			2500		22	40/2	EFC-1	5
2; 6	R-AMENITY 215 / OFFICE 217	20/1	23			730			2500	24	--	--	--
2	R-AMENITY 215 / AMENITY 220	20/1	25	720						26			
2	R-OFFICE 223 / 225 / AMENITY 215 / DATA 221	20/1	27		1080					28			
5	COPIER - AMENITY 215	20/1	29			1500			430	30	20/2	FC-2-1	5
5	UC REF - AMENITY 215	20/1	31	600			430			32	--	--	--
5	TELECOM BACKBOARD - DATA 221	20/1	33		360			586		34	20/2	FC-2-2	5
5	TELECOM BACKBOARD - DATA 221	20/1	35			360			586	36	--	--	--
2	R-DATA 221	20/1	37	360			586			38	20/2	FC-2-3	5
2	R-DATA 221	20/1	39		360			586		40	--	--	--
			41						172	42	20/2	BC-1	5
1; 6	L-RMS 102 / 103 / 105 / 107 / 111 / 114 / 119 / T100	20/1	43	439			172			44	--	--	--
			45					161		46	20/1	EF-22	6
1	L-LOBBY 100 / LEASING 101	20/1	47			452			560	48	20/1	CONDENSATE PUMPS - LVL 1 & 2	6
--	SPARE (20A/1P)	--	49	0			375			50	20/2	EWH-12	3
--	SPARE (20A/1P)	--	51		0			375		52	--	--	--
--	SPARE (20A/1P)	--	53			0			1176	54	20/1	SF-1	6
--	SPARE (20A/1P)	--	55	0			200			56	20/1	MECH CONTROL PANEL - UTILITY 206	5
--	SPARE (20A/1P)	--	57		0			200		58	20/1	VRF CENTRAL CONTROLLER - UTILITY 206	5
--	SPARE (20A/1P)	--	59			0			800	60	20/1	FSD - LVL 2-4 (SOUTH)	5
--	SPARE (20A/1P)	--	61	0			180			62	20/1	REPEATER - DATA 221	2
3	EWH-3	20/1	63		1500			500		64	20/1	EXTERIOR SIGN (MAIN ENTRY)	1
3	EWH-4	20/1	65			1500			0	66	--	SPARE (20A/1P)	--
3	EWH-6	20/1	67	1500			0			68	--	SPARE (20A/1P)	--
3	EWH-5	20/2	69		1500			200		70	20/1	RELAY PANEL RPA	5
--	--	--	71			1500			0	72	20/1	BLTC (SENSING)	1

LOAD CODE	TOTAL (VA)	FACTOR	CODE LOAD	PANEL TOTALS
1 LIGHTS:	1883 VA	125.00%	2354 VA	
2 RECEPTACLE:	9360 VA	100.00%	9360 VA	42948 **TOTAL LOAD (VA)**
3 HEATING:	8250 VA	125.00%	10313 VA	45481 **TOTAL DEMAND (VA)**
4 KITCHEN:	0 VA	0.00%	0 VA	119.2 **TOTAL LOAD (A)**
5 EQUIPMENT:	21323 VA	100.00%	21323 VA	126 **CODE DEMAND (A)**
6 MOTORS:	2132 VA	100.00%	2132 VA	
LM LARGEST MOTOR:	0 VA	0.00%	0 VA	
7 MISC.	0 VA	0.00%	0 VA	

Notes:
* FIRST 10 KVA +50% OF THE BALANCE
** 125% OF THE LARGEST MOTOR + THE BALANCE

Branch Panel

PANEL: 2H2B — MKE & ASSOCIATES, INC. — **MOUNTING:** SURFACE
FED BY: SDP-A — **BUS/MAIN** 400 MLO
LOC: RETAIL 151 — **VOLTS** 120/208 — **PHASE** 3 — **WIRE** 4

C	DESCRIPTION	A/P	No.	A	B	C	A	B	C	No.	A/P	DESCRIPTION	C
--	SPACE	--	1	0			1500			2	20/1	TREADMILL-AMENITY 210	5
2	R-CAR STACKER PITS	20/1	3		1080			1500		4	20/1	TREADMILL-AMENITY 210	5
2	R-LOBBY 110 / PARKING 112 / UTILITY 114	20/1	5			1080			1500	6	20/1	TREADMILL-AMENITY 210	5
6	SP-2	20/3	7	1080			1500			8	20/1	TREADMILL - AMENITY 210	5
--	--	--	9		1080			1200		10	20/1	ELLIPTICAL - AMENITY 210	5
--	--	--	11			1080			1200	12	20/1	ELLIPTICAL - AMENITY 210	5
6	SP-3	20/3	13	1080			1200			14	20/1	AIR RUNNER - AMENITY 210	5
--	--	--	15		1080			1200		16	20/1	UPRIGHT BIKE - AMENITY 210	5
--	--	--	17			1080			1200	18	20/1	ROWER - AMENITY 210	5
6	SP-4	20/3	19	1080			600			20	20/1	UC REF - AMENITY 210	5
--	--	--	21		1080			960		22	20/1	BOTTLE FILLER - AMENITY 215 ^	5
--	--	--	23			1080			800	24	20/1	FSD - LVL 2	5
5	AIR COMPRESSOR - TRASH T100	20/3	25	936			550			26	20/1	R-JANITOR 111 / EXIT 113	2; 6
--	--	--	27		936			360		28	20/1	R-LEASING 101 / WK RM 105	2
--	--	--	29			936			720	30	20/1	R-RESTROOM 107 / LOBBY 110 /MAIL 119	2
--	SPACE	--	31	0			480			32	20/1	KEY TRACK - WORK ROOM 105	5
--	SPACE	--	33		0			1500		34	20/1	COPIER - WORK ROOM 105	5
--	SPACE	--	35			0			600	36	20/1	REF - WORK ROOM 105	5
6	TRASH COMPACTOR - TRASH T100	20/3	37	1320			1000			38	20/1	DW - WORK ROOM 105	5
--	--	--	39		1320			360		40	20/1	R-WORK ROOM 105	2
--	--	--	41			1320			900	42	20/1	R-LEASING 101 / WORK ROOM 105	2
6	EF-1	20/3	43	936			720			44	20/1	FLR BOX - LOBBY 100	2
--	--	--	45		936			1080		46	20/1	R-LOBBY 100 / OFFICE 102	2
--	--	--	47			936			600	48	20/1	UC REF - LEASING 101	5
6	EF-27	20/1	49	1176			360			50	20/1	R-LOBBY 100	2
6	EF-28	20/1	51		1176			1500		52	20/1	PACKAGE CONCIERGE - PACKAGE 106	5
--	SPACE	--	53			0			1500	54	20/1	PACKAGE CONCIERGE - PACKAGE 106	5
6	CAR STACKER	40/3	55	2400			540			56	20/1	R-GENERATOR 100 / GARAGE	2
--	--	--	57		2400			200		58	20/1	TRASH CHUTE INTERLOCK - TRASH T100	5
--	--	--	59			2400			200	60	20/1	ODOR CONTROL - TRASH T100	5
6	CAR STACKER	40/3	61	2400			1000			62	20/1	MOTORIZED SHADES - LOBBY 100 / OFFICE 102	6
--	--	--	63		2400			0		64	--	SPARE (20A/1P)	--
--	--	--	65			2400			0	66	--	SPARE (20A/1P)	--
6	CAR STACKER	40/3	67	2400			0			68	--	SPARE (20A/1P)	--
--	--	--	69		2400			600		70	20/1	FSD - WATER 118 / LOBBY 100	5
--	--	--	71			2400			200	72	20/1	DATA COLLECTOR - WORK ROOM 105	5
6	BP-1a	110/3	73	11730			0			74	--	SPARE (20A/1P)	--
--	--	--	75		11730			0		76	--	SPARE (20A/1P)	--
--	--	--	77			11730			0	78	--	SPARE (20A/1P)	--
6	BP-1b	110/3	79	9384			0			80	--	SPARE (20A/1P)	--
--	--	--	81		9384			0		82	--	SPARE (20A/1P)	--
--	--	--	83			9384			0	84	--	SPARE (20A/1P)	--

LOAD CODE	TOTAL (VA)	FACTOR	CODE LOAD	PANEL TOTALS
1 LIGHTS:	0 VA	0.00%	0 VA	
2 RECEPTACLE:	7740 VA	100.00%	7740 VA	138080 **TOTAL LOAD (VA)**
3 HEATING:	0 VA	0.00%	0 VA	138080 **TOTAL DEMAND (VA)**
4 KITCHEN:	0 VA	0.00%	0 VA	383.3 **TOTAL LOAD (A)**
5 EQUIPMENT:	25548 VA	100.00%	25548 VA	383 **CODE DEMAND (A)**
6 MOTORS:	104792 VA	100.00%	104792 VA	
LM LARGEST MOTOR:	0 VA	0.00%	0 VA	
7 MISC.	0 VA	0.00%	0 VA	

Notes:
^ PROVIDE GFCI CIRCUIT BREAKER.
^^ BP-1a IS LARGEST MOTOR LOAD AND HAS BEEN CALCULATED AT 125% LOAD.
* FIRST 10 KVA +50% OF THE BALANCE
** 125% OF THE LARGEST MOTOR + THE BALANCE

Branch Panel

PANEL: 2H4 — MKE & ASSOCIATES, INC. — **MOUNTING:** SURFACE
FED BY: SDP-A — **BUS/MAIN** 200 FTL
LOC: ELECTRICAL E400 — **VOLTS** 120/208 — **PHASE** 3 — **WIRE** 4

C	DESCRIPTION	A/P	No.	A	B	C	A	B	C	No.	A/P	DESCRIPTION	C
2	R-NW WEST CORRIDOR (LEVEL 3-8)	20/1	1	1080			800			2	20/1	FSD - LVL 3-4 (NORTH)	5
2	R-W WEST CORRIDOR (LEVEL 3-8)	20/1	3		1080			800		4	20/1	FSD - LVL 5-6 (NORTH)	5
2	R-SW WEST CORRIDOR (LEVEL 3-8)	20/1	5			1080			800	6	20/1	FSD - LVL 7-8 (NORTH)	5
2	R-W CENTER CORRIDOR (LEVEL 3-8)	20/1	7	1080			800			8	20/1	FSD - LVL 5-8 (SOUTH)	5
2	R-CTR CENTER CORRIDOR (LEVEL 3-8)	20/1	9		1080			540		10	20/1	REPEATER - ELECTRICAL E300 / E400 / E500	2
2	R-E CENTER CORRIDOR (LEVEL 3-8)	20/1	11			1080			0	12	--	SPACE	--
2	R-EAST CORRIDOR (LEVEL 3-8)	20/1	13	1080			0			14	--	SPACE	--
2	R-ELEC ROOMS (LEVEL 3-8)	20/1	15		1080			0		16	--	SPACE	--
--	SPARE (20A/1P)	--	17			0			0	18	--	SPACE	--
--	SPARE (20A/1P)	--	19	0			0			20	--	SPACE	--
--	SPARE (20A/1P)	--	21		0			0		22	--	SPACE	--
--	SPARE (20A/1P)	--	23			0			0	24	--	SPACE	--
--	SPARE (20A/1P)	--	25	0			0			26	--	SPACE	--
--	SPARE (20A/1P)	--	27		0			0		28	--	SPACE	--
--	SPARE (20A/1P)	--	29			0			0	30	--	SPACE	--
--	SPARE (20A/1P)	--	31	0			0			32	--	SPACE	--
--	SPARE (20A/1P)	--	33		0			0		34	--	SPACE	--
--	SPARE (20A/1P)	--	35			0			0	36	--	SPACE	--
--	SPARE (20A/1P)	--	37	0			0			38	--	SPACE	--
--	SPARE (20A/1P)	--	39		0			0		40	--	SPACE	--
--	SPARE (20A/1P)	--	41			0			0	42	--	SPACE	--

LOAD CODE	TOTAL (VA)	FACTOR	CODE LOAD	PANEL TOTALS
1 LIGHTS:	0 VA	0.00%	0 VA	
2 RECEPTACLE:	9180 VA	100.00%	9180 VA	12380 **TOTAL LOAD (VA)**
3 HEATING:	0 VA	0.00%	0 VA	12380 **TOTAL DEMAND (VA)**
4 KITCHEN:	0 VA	0.00%	0 VA	34.4 **TOTAL LOAD (A)**
5 EQUIPMENT:	3200 VA	100.00%	3200 VA	34 **CODE DEMAND (A)**
6 MOTORS:	0 VA	0.00%	0 VA	
LM LARGEST MOTOR:	0 VA	0.00%	0 VA	
7 MISC.	0 VA	0.00%	0 VA	

Notes:
* FIRST 10 KVA +50% OF THE BALANCE
** 125% OF THE LARGEST MOTOR + THE BALANCE

Branch Panel

PANEL: 2H7 — MKE & ASSOCIATES, INC. — **MOUNTING:** SURFACE
FED BY: SDP-A — **BUS/MAIN** 200 MLO
LOC: ELECTRICAL E700 — **VOLTS** 120/208 — **PHASE** 3 — **WIRE** 4

C	DESCRIPTION	A/P	No.	A	B	C	A	B	C	No.	A/P	DESCRIPTION	C
5	FIRE PIT - ROOF TERRACE	20/1	1	200			334			2	20/1	L-CLUB ROOM B 821 / CLUB ROOM A 822	1
5	GAS BBQ - ROOF TERRACE	20/1	3		400			0		4	--	SPARE (20A/1P)	--
2	R - ROOF TERRACE ^	20/1	5			180			0	6	--	SPARE (20A/1P)	--
2	R - ELEV VEST R900 / ROOF TERRACE	20/1	7	360			0			8	--	SPARE (20A/1P)	--
2; 5	RECEPTACLE / IRRIGATION CONTROL - WTR HTR 902	20/1	9		380			0		10	--	SPARE (20A/1P)	--
2	REPEATER - ELECTRICAL E600 / E700 / E800	20/1	11			540			0	12	--	SPARE (20A/1P)	--
2	FLR BOX - CLUB ROOM B 821	20/1	13	1080			0			14	--	SPARE (20A/1P)	--
2	R-CLUB ROOM A 822	20/1	15		180			0		16	--	SPARE (20A/1P)	--
2	R-CLUB ROOM B 821	20/1	17			900			0	18	--	SPACE	--
5	REF - CLUB ROOM B 821	20/1	19	1200			0			20	--	SPACE	--
5	ICE MAKER - CLUB ROOM B 821	20/1	21		1000			0		22	--	SPACE	--
5	DW - CLUB ROOM B 821	20/1	23			1200			0	24	--	SPACE	--
2	R-CLUB ROOM B 821	20/1	25	360			0			26	--	SPACE	--
2	R-CLUB ROOM B 821	20/1	27		180			0		28	--	SPACE	--
2; 6	R-CLUB ROOM B 821 / A 822 / EF-25	20/1	29			910			0	30	--	SPACE	--
2	R-CLUB ROOM A 822	20/1	31	900			0			32	--	SPACE	--
--	SPARE (20A/1P)	--	33		0			0		34	--	SPACE	--
--	SPARE (20A/1P)	--	35			0			0	36	--	SPACE	--
--	SPARE (20A/1P)	--	37	0			110			38	20/1	L-LANDSCAPE / BBQ TASK (ROOF TERR) / TERR 821B	1
5	OVEN - CLUB ROOM B 821	40/2	39		2500			200		40	20/1	RELAY PANEL RPB	5
--	--	--	41			2500			0	42	20/1	BLTC SENSING	1

LOAD CODE	TOTAL (VA)	FACTOR	CODE LOAD	PANEL TOTALS
1 LIGHTS:	444 VA	125.00%	555 VA	
2 RECEPTACLE:	5760 VA	100.00%	5760 VA	15614 **TOTAL LOAD (VA)**
3 HEATING:	0 VA	0.00%	0 VA	15725 **TOTAL DEMAND (VA)**
4 KITCHEN:	0 VA	0.00%	0 VA	43.3 **TOTAL LOAD (A)**
5 EQUIPMENT:	9400 VA	100.00%	9400 VA	44 **CODE DEMAND (A)**
6 MOTORS:	10 VA	100.00%	10 VA	
LM LARGEST MOTOR:	0 VA	0.00%	0 VA	
7 MISC.	0 VA	0.00%	0 VA	

Notes:
^ GFCI CIRCUIT BREAKER.
* FIRST 10 KVA +50% OF THE BALANCE
** 125% OF THE LARGEST MOTOR + THE BALANCE

Branch Panel

PANEL: 2H7M — MKE & ASSOCIATES, INC. — **MOUNTING:** SURFACE
FED BY: SDP-A — **BUS/MAIN** 400 MLO
LOC: ELECTRICAL E700 — **VOLTS** 120/208 — **PHASE** 3 — **WIRE** 4

C	DESCRIPTION	A/P	No.	A	B	C	A	B	C	No.	A/P	DESCRIPTION	C
6	RCP-1	20/1	1	215			12360			2	125/3	RTU-1	5
--	SHUNT TRIP	--	3		0			12360		4	--	--	--
5	WH-1a	20/1	5			600			12360	6	--	--	--
--	SHUNT TRIP	--	7	0			12360			8	125/3	RTU-2	5
5	WH-1b	20/1	9		600			12360		10	--	--	--
--	SHUNT TRIP	--	11			0			12360	12	--	--	--
5	WH-1c	20/1	13	600			5160			14	60/3	RTU-3	5
--	SHUNT TRIP	--	15		0			5160		16	--	--	--
5	WH-1d	20/1	17			600			5160	18	--	--	--
--	SHUNT TRIP	--	19	0			6240			20	90/3	HP-1A	6
5	WH-1e	20/1	21		600			6240		22	--	--	--
--	SHUNT TRIP	--	23			0			6240	24	--	--	--
5	WH-1f	20/1	25	600			5160			26	70/3	HP-1B	6
--	SHUNT TRIP	--	27		0			5160		28	--	--	--
5	WH-3	20/1	29			1400			5160	30	--	--	--
--	SPACE	--	31	0			375			32	20/2	EWH-13	3
--	SPACE	--	33		0			375		34	--	--	--
--	SPARE (20A/1P)	--	35			0			0	36	--	SPARE (20A/1P)	--
--	SPARE (20A/1P)	--	37	0			0			38	--	SPARE (20A/1P)	--
2	R-ROOF (WEST)	20/1	39		900			0		40	--	SPARE (20A/1P)	--
2	R-ROOF (EAST)	20/1	41			1080			0	42	--	SPARE (20A/1P)	--

LOAD CODE	TOTAL (VA)	FACTOR	CODE LOAD	PANEL TOTALS
1 LIGHTS:	0 VA	0.00%	0 VA	
2 RECEPTACLE:	1980 VA	100.00%	1980 VA	131785 **TOTAL LOAD (VA)**
3 HEATING:	750 VA	125.00%	938 VA	131973 **TOTAL DEMAND (VA)**
4 KITCHEN:	0 VA	0.00%	0 VA	365.8 **TOTAL LOAD (A)**
5 EQUIPMENT:	94640 VA	100.00%	94640 VA	366 **CODE DEMAND (A)**
6 MOTORS:	34415 VA	100.00%	34415 VA	
LM LARGEST MOTOR:	0 VA	0.00%	0 VA	
7 MISC.	0 VA	0.00%	0 VA	

Notes:
* FIRST 10 KVA +50% OF THE BALANCE
** 125% OF THE LARGEST MOTOR + THE BALANCE

TYP. UNIT PANELS		
	2H2A	2H4
	2H2B	2H7
		2H7M

City Of Portland
REVIEWED FOR CODE COMPLIANCE
Date: 02/11/20
Project: 19-106743-REV-01-CO

Bergelectric Corp.
Sustainable Engineering
13650 Ne Whitaker Way
Portland, OR 97230
License #C10-65046
Phone: (503) 255-1818

PROPRIETARY STATEMENT:
THE ELECTRICAL DESIGN/CALCULATIONS ON THESE DOCUMENTS ARE FOR THE EXCLUSIVE PROPERTY OF BERGELECTRIC CORP. (CORPORATION). THESE DOCUMENTS ARE NOT TO BE USED FOR CONSTRUCTION PURPOSES UNLESS SIGNED FOR CONTRACT. COPIES OF THIS DOCUMENT WITHOUT WRITTEN CONSENT OF BERGELECTRIC CORPORATION IS STRICTLY PROHIBITED. ALL RIGHTS RESERVED.